










PS-12330 12V 33.0 AH @ 20-hr. 12V 30.0 AH @ 10-hr.

Rechargeable Sealed Lead Acid Battery PS – General Purpose Series

TERMINALS: (mm)



Torque: 3.9~5.4 Nxm

DIMENSIONS: inch (mm)

θ

сTT

0

Ø


Œ

СП

0

€3

6



This model can be supplied with T6 button terminals, subject to inventory availability and lead in times.

7.72 (196)

5.14 (131) 6.22 (158)

Tolerances are +/- 0.04 in. (+/- 1mm) and +/- 0.08 in. (+/- 2mm) for height

dimensions. All data subject

Н

to change without notice.

L:

W:

H: 6.22 (158) HT: 7.00 (176)

W

HT

FEATURES

- Absorbent Glass Mat (AGM) technology for superior performance
- Valve regulated, maintenance free spill proof construction
- Power/volume ratio yielding excellent energy density
- Rugged vibration and impact resistant ABS case and cover
- Gas recombination technology
- 5 year design life

APPROVALS

- Approved for transport by air. D.O.T., I.A.T.A., F.A.A. and C.A.B. certified
- U.L. recognized
- ISO9001:2015 Quality management systems

PERFORMANCE SPECIFICATIONS

Nominal Voltage	12 volts (6 cells)
Nominal Capacity 20-hr. (1.65A to 10.50 volts) 10-hr. (3.00A to 10.50 volts) 5-hr. (5.20A to 10.20 volts) 1-hr. (19.8A to 9.00 volts)	33.0 AH 30.0 AH 26.0 AH 19.8 AH
Approximate Weight	23.0 lbs. (10.5 kg)
Internal Resistance (approx.)	10.0 milliohms
Max Short-Duration Discharge Current (10 Sec.)	330.0 amperes
Shelf Life (% of nominal capacity at 68°F (20°C) 1 Month 3 Month 6 Month	97% 91% 83%
Operating Temperature Range Charge Discharge	5°F (-15°C) to 122°F (50°C) -4°F (-20°C) to 140°F (60°C)
Case	ABS Plastic
Power Sonic Chargers	PSC-124000-PC PSC-124000A-C

CORPORATE HEADQUARTERS (USA AND INTERNATIONAL EXCLUDING EMEA)

Т

POWER

MODEL PS-12330 NB 12 Volt 33.0 Amp. Hr.

Power-Sonic Corporation 7550 Panasonic Way, San Diego, California 92154

- **T:** +1 (619) 661 2020
- 1: +1 (619) 661 202
- **F:** +1 (619) 661 3650
- E: customer-service@power-sonic.com
- 3 Buckingham Square, Hurricane Way, Wickford, Essex SS11 8YQ
- **T:** +44 (0)1268 560686 **F:** +44 (0)1268 560902
- F. +44 (U) 1268 560902

POWER-SONIC EUROPE LIMITED

(EMEA - EUROPE, MIDDLE EAST AND AFRICA)

E: salesEMEA@power-sonic.com

To ensure safe and efficient operation always refer to the latest edition of our Technical Manual, as published on our website. © 2018. Power-Sonic Corporation. All rights reserved. All trademarks are the property of their respective owners. All data subject to change without notice. E&O.E


power-sonic.com



PS-12330 12V 33.0 AH @ 20-hr. 12V 30.0 AH @ 10-hr.

Rechargeable Sealed Lead Acid Battery PS – General Purpose Series

LIFE CHARACTERISTICS IN STAND-BY USE



CHARGERS

Power Sonic offers a wide range of chargers suitable for batteries with a variety of capacities.

Please refer to our website for more information on our switch mode and transformer type chargers.


Please contact our technical department for advice if you have difficulty in locating a suitable charger.

FURTHER INFORMATION

Please refer to our website www.power-sonic.com for a complete range of useful downloads, such as product catalogs, material safety data sheets (MSDS), ISO certification, etc.



SHELF LIFE & STORAGE



CHARGING

Cycle Applications: Apply constant voltage charge at 2.35v/c - 2.45v/c (14.1 - 14.7v for 12v Monobloc) at 20°C. Initial charging current should be set at less than 0.25C Amps. Switch to float charge to avoid overcharging.

"Float" or "Stand-By" Service: Apply constant voltage charge of 2.25v/c - 2.30v/c (13.5 to 13.8 volts for 12v Monobloc at 20°C. When held at this voltage, the battery will seek its own current level and maintain itself in a fully charged condition.

Temperature Compensation: Charging Voltage for both Cyclic and Standby applications should be regulated in relation to ambient temperature. As temperature rises charging voltage should be reduced to prevent overcharge and increased as temperature falls to avoid undercharge.

For further charging information including temperature compensation factors, see Power Sonic Technical Manual/ Power Sonic Charger specifications.

APPLICATIONS

- General purpose
- Emergency lighting
- Medical
- Fire and security

CORPORATE HEADQUARTERS (USA AND INTERNATIONAL EXCLUDING EMEA)

Power-Sonic Corporation 7550 Panasonic Way, San Diego, California 92154 T: +1 (619) 661 2020 F: +1 (619) 661 3650

- E: customer-service@power-sonic.com

Essex SS11 8YQ T: +44 (0)1268 560686 F: +44 (0)1268 560902 E: salesEMEA@power-sonic.com

3 Buckingham Square,

Hurricane Way, Wickford,

POWER-SONIC EUROPE LIMITED

(EMEA - EUROPE, MIDDLE EAST AND AFRICA)

To ensure safe and efficient operation always refer to the latest edition of our Technical Manual, as published on our website © 2018. Power-Sonic Corporation. All rights reserved. All trademarks are the property of their respective owners All data subject to change without notice. E&O.E

power-sonic.com